



RF360
Europe GmbH

SDST (SAW DEVICE SELECTION TABLE)

SAW RF filter and resonator

Automotive Electronics

Automotive Applications: Remote Keyless Entry Systems
Tire Pressure Monitoring Systems
Automotive Telematics Applications
GPS in Automotive Applications
Digital Radio Applications

Non Automotive Applications: Garage Door Openers
Wireless Switches & Smart Home Applications
Smart Grid Applications
Wireless Audio Applications
Security and Alarm Systems
Wireless Access & Tagging Systems
Medical Applications

Content:	1. Narrowband Filters for ISM	3
	2. Wideband Filters for ISM	5
	3. Filter for GNSS	7
	4. Filter for Telematics Communication (se/se)	9
	5. Diplexers, band-stop filters and extractors for GNSS, digital radio and metering	11
	6. Bandpass filters for Digital Radio	12
	7. Resonators for ISM	13

RF360 products mentioned within this document are products of RF360 Europe GmbH and other subsidiaries of RF360 Holdings Singapore Pte. Ltd. (collectively, the "RF360 Subsidiaries").

RF360 Holdings Singapore Pte. Ltd. is a joint venture of Qualcomm Global Trading Pte. Ltd. and EPCOS AG.

RF360 Europe GmbH, Anzinger Str. 13, Munchen, Germany

© 2019 RF360 Europe GmbH and/or its affiliated companies. All rights reserved.

These materials, including the information contained herein, may be used only for informational purposes by the customer. The RF360 Subsidiaries assume no responsibility for errors or omissions in these materials or the information contained herein. The RF360 Subsidiaries reserve the right to make changes to the product(s) or information contained herein without notice. The materials and information are provided on an AS IS basis, and the RF360 Subsidiaries assume no liability and make no warranty or representation, either expressed or implied, with respect to the materials, or any output or results based on the use, application, or evaluation of such materials, including, without limitation, with respect to the non-infringement of trademarks, patents, copyrights or any other intellectual property rights or other rights of third parties.

No use of this documentation or any information contained herein grants any license, whether express, implied, by estoppel or otherwise, to any intellectual property rights, including, without limitation, to any patents owned by QUALCOMM Incorporated or any of its subsidiaries.

Not to be used, copied, reproduced, or modified in whole or in part, nor its contents revealed in any manner to others without the express written permission of RF360 Europe GmbH.

Qualcomm is a trademark of Qualcomm Incorporated, registered in the United States and other countries. Other product and brand names may be trademarks or registered trademarks of their respective owners.

This technical data may be subject to U.S. and international export, re-export, or transfer ("export") laws. Diversion contrary to U.S. and international law is strictly prohibited.

Narrowband Filter for ISM (high temperature stability)

Center Frequency MHz	Type		Usable Passband MHz	Insertion Attenuation dB	Package size mm*mm	Feature	DS link
169.5	B39171 B3942 U310		0.20	1.9	5*5		B3942
313.15			0.20	2.6			
314.00	B39311 B3534 A410		0.20	2.7	3.8*3.8	Triplexer	B3534
314.925			0.39	2.7			
313.15	B39311 B3535 A410		0.20	2.3	3.8*3.8	Diplexer	B3535
314.00			0.20	2.3			
313.15	B39311 B3538 H110		0.18	2.6	3*3	Diplexer	B3538
314.00			0.18	2.3			
313.85	B39314 B3931 H110		0.76	2.3	3*3	Wide passband	B3931
313.85	B39311 B3768 Z810		0.36	1.9	3.8*3.8		B3768
313.15	B39311 B3955 H110	o	0.18	2.2	3*3	Comb filter	
314.00			0.18	2.2			
313.85	B39321 B3787 A410		0.76	2.6	3.8*3.8	Comb filter	B3787
315.00			0.36	2.7			
313.85	B39321 B3958 H110	o	0.76	2.6	3*3	Comb filter	
315.00			0.36	2.7			
314.45	B39311 B3950 H110		1.10	2.2	3*3		B3950
314.45	B39311 B3784 Z810		1.10	1.9	3.8*3.8		B3784
314.90	B39311 B3739 H110		0.36	2.3	3*3		B3739
315.00	B39321 B3741 H110		0.36	2.1	3*3		B3741
315.00	B39321 B3761 Z810		0.36	1.9	3.8*3.8		B3761
315.00	B39321 B3781 Z810		0.55	1.7	3.8*3.8		B3781
315.00	B39321 B3783 Z810		1.10	1.9	3.8*3.8		B3783
400.00	B39401 B3742 H110		0.25	2.3	3*3		B3742
426.08	B39431 B3770 Z810		0.15	2.0	3.8*3.8		B3770
433.20			0.18	2.8			
433.92	B39431 B3532 A410		0.26	2.9	3.8*3.8	Triplexer	B3532
434.64			0.18	2.9			
433.20	B39431 B3537 H110		0.18	2.3	3*3	Diplexer	B3537
434.64			0.18	2.3			
433.20	B39431 B3533 A410		0.18	2.3	3.8*3.8	Diplexer	B3533
434.64			0.18	2.4			
433.42	B39431 B3735 H110		0.36	2.1	3*3		B3735
433.42	B39431 B3791 Z810		0.24	3.8	3.8*3.8	external coupling coil; high ultimate rejection	B3791
433.58	B39431 B3536 A410		0.30	2.5	3.8*3.8	Diplexer	B3536
434.30			0.30	2.6			
433.60	B39431 B3953 H110		0.6	2.1	3*3		B3953
433.92	in dev.	new	0.36	0.6-1.2	2.5*2.0		
433.92	B3301	new	0.34	1.9	3*3	2-5 pinning	B3301
433.92	B39431 B3732 H110		0.36	2.4	3*3	high selectivity at fc-2 MHz	B3732
433.92	B39431 B3743 H110		0.34	1.9	3*3	low insertion attenuation	B3743
433.92	B39431 B3760 Z810		0.36	1.9	3.8*3.8		B3760
433.92	B39431 B3774 Z810		0.36	2.4	3.8*3.8	high selectivity at fc-2 MHz	B3774
433.92	B39431 B3790 Z810		0.12	3.6	3.8*3.8	external coupling coil; high ultimate rejection	B3790
433.92	B39431 B3780 Z810		0.55	2.0	3.8*3.8		B3780
433.92	B39431 B3782 Z810		1.10	2.2	3.8*3.8	high usable bandwidth	B3782
433.92	B39431 B3951 H110		1.10	2.2	3*3		B3951

Narrowband Filter for ISM (high temperature stability)

Center Frequency MHz	Type	Usable Passband MHz	Insertion Attenuation dB	Package size mm*mm	Feature	DS link
433.92	B39431 B3933 H110	0.12	3.1	3*3	high nearby rejection	B3933
433.92	B39431 B3935 H110	1.06	2.2	3*3	high usable bandwidth	B3935
433.92	B39431 B3936 H110	0.55	2.2	3*3		B3936
434.17	B39431 B3932 H110	0.78	2.4	3*3		B3932
434.42	B39431 B3733 H110	0.36	2.1	3*3	high selectivity at fc-2 MHz	B3733
434.42	B39431 B3748 H110	0.36	1.9	3*3		B3748
868.30	B39871 B3734 H110	0.30	3.2	3*3	high RFID rejection	B3734
868.30	B39871 B3744 H110	0.60	3.0	3*3		B3744
868.60	B39871 B3746 H110	1.20	2.6	3*3		B3746
868.95	B39871 B3941 H110	0.50	3.2	3*3		B3941
869.30	B39871 B3749 H110	1.40	2.7	3*3		B3749
902.875	B39901 B3934 H110	1.55	2.4	3*3		B3934
916.50	B39921 B3300 H110	1.20	2.7	3*3		B3300
921.42	B39921 B3949 H110	0.30	3.4	3*3	Z-Wave	B3949
924.15	B39921 B3419 U410	7.10	2.0	3*3	low IL; low amplitude ripple	B3419
928.35	B39931 B3758 H110	0.50	3.6	3*3		B3758

Wideband Filter for ISM

Center Frequency MHz	Type	Remark	Usable Passband MHz	Insertion Attenuation dB	Package size mm*mm	Feature	DS link
313.60	B39311B3403H110		3.3	1.5	3*3	50Ω; pinning 1-4	B3403
313.85	B39311B3713U410		0.60	1.7	3*3	50Ω	B3713
313.85	B39311B3729H110		1.0	1.5	3*3	50Ω; pinning 1-4	B3729
314.35	B39311B3714U410		0.60	1.9	3*3	50Ω	B3714
314.45	B39182B2607P810	new	1.3	1.1	1.8*1.4	Filter with focus on harmonics suppression and very low IL	B2607
315.00	B39321B3719H110		1.0	1.4	3*3	50Ω; pinning 1-4	B3719
315.00	B39321B3722U410		1.0	1.5	3*3	50Ω	B3722
315.00	B39321B3905U510		1.0	1.3	3*3	50Ω se/200Ω bal	B3905
345.00	B39351B3408U410		0.8	2.5	3*3	50Ω	B3408
428.00	B39431B3411U410		16.0	2.0	3*3	50Ω	B3411
433.92	B39182B2608P810	new	1.3	1.1	1.8*1.4	Filter with focus on harmonics suppression and very low IL	B2608
433.92	B39431B3710U410		1.7	2.0	3*3	50Ω	B3710
433.92	B39431B3721U410		1.6	2.6	3*3	50Ω; high selectivity	B3721
433.92	B39431B3727H110		1.7	2.8	3*3	50 Ω, pinning 1-4, high nearby rejection	B3727
433.92	B39431B3900U410		0.4	1.2	3*3	50Ω	B3900
433.92	B39431B3925U410		0.4	1.7	3*3	50Ω; high nearby rejection	B3925
433.92	B39431B3402H110		0.3	1.7	3*3	50Ω; pinning 1-4	B3402
447.70	B39451B3907U410		1.6	3.0	3*3	50Ω	B3907
454.50	B39451B3422U410		2.0	2.8	3*3	50Ω	B3422
480.00	B39481B3427U410	special	20.0	1.7	3*3	Rx co-design with Tx B3426 for duplexing	B3427
505.00	B39511B3426U410	special	10.0	1.7	3*3	Tx co-design with Rx B3427 for duplexing	B3426
480 / 505	in dev.	new	20 / 10	2.0 / 2.0	2.5*2.0	Duplexer	
760.00	B39761B3445U510	special	8.3	2.3	3*3	50Ω; High out-of-band attenuation; Temperature compensation	B3445
760.00	B39761B3928U510		8.3	3.0	3*3	50Ω se/100Ω bal	B3928
845.00	B39851B3438U410		12.0	1.4	3*3	high power for smart metering	B3438
866.50	B39871B4377P810		7.0	2.3	1.4*1.1	improved LSB attenuation; small size	B4377
866.50	B39871B3420U410	o	7.0	1.8	3*3	high power durability	
866.50	B39871B3717U410		7.0	2.2	3*3	50Ω	B3717
866.80	B39871B3441U410	special	2.4	3.4	3*3	50Ω; high nearby rejection Temperature compensation	
869.00	in dev.	special new	2.0	2.7	3*3	very high attenuation up to 70dB Temperature compensation, no AEC-Q200	
869.00	B39871B2600P810		14.0	1.6	1.4*1.1	Low-loss RF filter for smart metering	B2600
869.00	B39871B3430U410		10.0	2.0	3*3	Low-loss RF filter for smart metering	B3430
869.00	B39871B4365P810	special	2.0	2.5	1.4*1.1	no AEC-Q200; Temperature compensation	B4365
869.00	B39871B3440U410	special	2.0	2.6	3*3	50Ω improved LTE suppr. Temperature compensation	B3440
869.00	B39871B3725U410		2.0	2.5	3*3	50Ω; high nearby rejection	B3725
869.00	B39871B3903U510		2.0	1.4	3*3	50Ω se/200Ω bal	B3903
869.00	B39871B4316P810		2.0	2.0	1.4*1.1	50Ω; small size	B4316
869.00	in dev.	new	2.0	1.9	1.4*1.1	no AEC-Q200, for indoor application	
869.00	in dev.	new	2.0	2.7	1.4*1.1	50Ω; small size	
872.00	B39871B3443U410	special	8.0	3.0	3*3	50Ω; extended passband Temp. Comp.	B3443
908.50	B39911B3429U410		13.0	2.0	3*3	steep righ skirt Rx co-design with B3433 for duplexing	B3429
915.00	B39921B3434U410	new	10.0	2.2	3*3	steep righ skirt	B3434
915.00	B39921B3726U410		10.0	2.6	3*3	50Ω	B3726
915.00	B39921B3435U410		12.0	1.6	3*3	low IL; se/bal	B3435
915.00	B39921B4379U810		26.0	1.9	1.1*0.9	small size	B4379
915.00	B39921B4301F210		26.0	1.5	1.4*1.1	50Ω; small size	B4301
915.00	B39921B4344P810		26.0	2.8	1.4*1.1	50Ω; small size	B4344
915.00	B39921B2672P810		26.0	1.1	1.4*1.1	no AEC-Q200, for indoor application	B2672
915.00	B39921B3728U410		26.0	2.2	3*3	50Ω	B3728
915.00	B39921B4317P810		26.0	1.7	1.4*1.1	50Ω se/200Ω bal	B4317
915.00	B2625	new	26.0	1.7	1.4*1.1	50Ω	B2625

Wideband Filter for ISM

Center Frequency MHz	Type	Remark	Usable Passband MHz	Insertion Attenuation dB	Package size mm*mm	Feature	DS link
915.00	B39921 B2671 P810	new	26.0	1.5	1.1*0.9	no AEC-Q200, for indoor application	B2671
915.70	B39921 B3432 U410		5.8	0.6	3*3	50Ω; low IL 0.9dB max	B3432
916.00	B39921 B3718 U410		3.5	2.4	3*3	50Ω	B3718
921.50	B39921 B2615 P810	new	13.0	1.4	1.4*1.1	50Ω	B2615
922.50	B39921 B2619 P810	new	5.0	1.4	1.4*1.1	50Ω	B2619
922.50	B39921 B3407 U410		5.0	1.5	3*3	50Ω	B3407
924.50	B39921 B2616 P810	new	5.0	2.1	1.4*1.1	50Ω	B2616
925.00	B39931 B3446 U410	special	4.0	2.0	3*3	50Ω; Temperature compensation	B3446
925.00	B39931 B3919 U410		3.2	1.4	3*3	50Ω	B3919
925.15	B39931 B4336 P810		5.9	1.7	1.4*1.1	50Ω	B4336
925.20	B39931 B3926 U410		5.8	1.4	3*3	50Ω	B3926
925.50	B39931 B3433 U410	special	5.0	2.2	3*3	50Ω; Tx co-design with B3429 for Duplexing	B3433
925.80	B39931 B3916 U410		4.6	0.6	3*3	50Ω; low IL 0.9dB max	B3916
925.80	B39931 B3921 U410		4.6	1.6	3*3	50Ω; high selectivity	B3921
2441.75	B39242 B4347 P810		83.5	1.7	1.4*1.1	50Ω; Wifi filter with high suppression at SDARS	B4347
2441.75	B39242 B3918 U410		83.5	1.9	3*3	50Ω; Wifi filter with high suppression at SDARS	B3918
2441.75	B39242 B4360 P810		83.5	2.1	1.1*0.9	50Ω	B4360
2442.00	B39242 B4346 P810	special	79.0	1.9	1.4*1.1	50Ω BAW	Sales
2442.00	B39242 B2614 P810	ewspecial	79.0	1.2-1.5	1.1*0.9	50Ω BAW	Sales
2448.50	B39242 B3912 U410		97.0	1.7	3*3	50Ω	B3912

Filter for GNSS

Start Freq MHz	Stop Freq MHz	Center Freq MHz	Type	Remark	Usable Passband MHz	Insertion Attenuation dB	Package size mm*mm	Application	DS link
1166.22	1249.14	1207.5	B39122B2627P810	new	82.92	1.9-2.6	1.1*0.9	GNSS L5+E5+G3+L2+G2	Sales
1166.45	1186.45	1176.45	B39122B3452U410		20	1.3	3*3	GNSS E5a (QZSS L5)	Sales
1196	1250	1223	B39122B3596U410		54	2.0	3*3	GNSS E5b+G3+L2+G2; High selectivity; Low GDR; Dashboard	Sales
1197	1249	1223	in dev.	new	52	1.0-1.3	1.1*0.9	GNSS E5b+G3+L2+G2; Low GDR; Low IA	Sales
1197	1249	1223	B39122B2620P810	new	52	1.1-1.5	1.4*1.1	GNSS E5b+G3+L2+G2; Low GDR; High Att.	Sales
1215	1254	1234.5	B39122B3439U410	new	39	1.5	3*3	GNSS L2+G2	Sales
1273.75	1283.75	1278.75	B39132B3428U410		10	1.5	3*3	GNSS E6 (QZSS L6)	Sales
1525	1559	1542.00	B39152B3421U410		34	1.4	3*3	GNSS L	B3421
1525	1605.9	1565.50	in dev.	new	80.9	1.2-1.5	1.4*1.1	GNSS L+L1+E1+G1+B1; Low GDR; Low IA	
1525	1606	1565.50	B39232B3424U410		81	2.0	3*3	GNSS L+L1+E1+G1+B1 Low GDR; Dashboard	Sales
1559	1582.5	1606	B2631	new	7	1.1	1.4*1.1	GNSS L1+E1+G1+B1 low GDR; Low IA	B2631
1559	1616	1588.00	B39162B3412U410		57	1.8	3*3	GPS/Galileo/Glonass/BeiDou	B3412
1559	1616	1587.50	B39162B3413U410		57	2.0	3*3	GPS/Galileo/Glonass/BeiDou improved ESD robustness	B3413
1559	1606	1582.50	B39162B3415U410		47	2.0	3*3	GPS/Galileo/Glonass/BeiDou High att. at 1450 to 1525 MHz	B3415
1559	1605.7	1582.35	B39163B3431B710		46.7	1.3-1.6	2.5*2	GPS/Galileo/Glonass/BeiDou	B3431
1559.05	1605.89	1582.47	B39162B2617P810		46.8	0.8-1.4	1.4*1.1	GPS/Galileo/Glonass/BeiDou 50Ωse/100Ωbal; Low GDR	B2617
1559.05	1605.89	1582.47	B39162B2618P810		46.8	1.4	1.1*0.9	GPS/Galileo/Glonass/BeiDou Out of Band selec.; post LNA	B2618
1559.05	1605.89	1582.47	B39162B2611P810		46.8	0.9	1.1*0.9	GPS/Galileo/Glonass/BeiDou small size; low IL; pre LNA	B2611
1559.05	1605.66	1582.40	B39162B4327P810	o	46.61	1.4	1.4*1.1	GPS/Galileo/Glonass/BeiDou	
1559.05	1605.89	1582.47	B39162B4348P810		46.8	0.8	1.4*1.1	GPS/Galileo/Glonass/BeiDou; Top =105C	B4348
1559.05	1605.66	1582.40	B39162B4353P810		46.61	1.0-1.5	1.4*1.1	GPS/Galileo/Glonass/BeiDou; Top =125C	B4353
1560	1606	1583.00	B39162B3423U410		46	2.0	3*3	GNSS L1+E1+G1+B1 High selectivity; Low GDR; Dashboard	B3423
1560	1616	1588.00	B39162B3913U410		56	2.0	3*3	GPS/Galileo/Glonass/BeiDou	B3913
1565	1606	1585.50	B39162B3519U410		41	1.9	3*3	GPS/Galileo/Glonass	B3519
1565.42	1605.89	1585.60	B39162B3414U510		40.47	2.1	3*3	GPS/Galileo/Glonass 50Ωse/100Ωbal; High att. at 1625 MHz	B3414
1571.42	1605.89	1588.65	B39162B3401B710		34.47	1.6	2*2.5	GPS/Galileo/Glonass	B3401
1572.42	1578.42	1575.42	B39162B3524B710		6.0	1.4	2.5*2	GPS/Galileo; 50Ωse/50Ωse	B3524
1572.42	1578.42	1575.42	B39162B3525U510	o	6.0	2.8	3*3	GPS/Galileo 50Ωse/100Ωbal; high selectivity; post LNA	
1572.42	1578.42	1575.42	B39162B3923U410		6.0	1.3	3*3	GPS/Galileo; low IA; pre LNA	B3923
1573.42	1605.89	1588.655	B39162B4310P810		34.47	1.5	1.4*1.1	GPS/Galileo/Glonass; Low IA; pre LNA	B4310
1573.42	1605.89	1588.655	B39162B4313P810		34.47	1.6	1.4*1.1	GPS/Galileo/Glonass 50Ωse/100Ωbal; high selectivity; post LNA	B4313
1573.92	1576.92	1575.42	B39162B4300F210		3.0	1.2	1.4*1.1	GPS/Galileo; low IA	B4300
1574.4	1576.44	1575.42	B39162B3400U410		2.0	2.3	3*3	GPS/Galileo; High nearby rejection	B3400
1574.42	1576.42	1575.42	B39162B3528U510		2.0	1.2	3*3	GPS/Galileo; 50Ωse/100Ωbal; low IA	B3528
1574.42	1576.42	1575.42	B39162B4308P810		2.0	1.3	1.4*1.1	GPS/Galileo; 50Ωse/100Ωbal; low IA	B4308

Diplexer / Comb filter

Start Freq MHz	Stop Freq MHz	Center Freq MHz	Type	Remark	Usable Passband MHz	Insertion Attenuation dB	Package size mm*mm	Application	DS link
1164	1218	1191	B39162B3504U410	new	54	2.0	3*3	GNSS L1+E1+G1+B1 / L5+E5+G3 comb filter	Sales
1559	1606	1582.5	in dev.	new	47	2.7	3*3	GNSS L1+E1+G1+B1 / L5+E5+G3+L2 comb filter; High Attenuation; Low GDR	Sales
1164	1250	1207	in dev.	new	86	2.4	3*3	GNSS L1+E1+G1+B1 / L5+E5a comb Filter; Low GDR	Sales
1559	1606	1582.5	in dev.	new	47	2.8	3*3	GNSS L1+E1+G1+B1 / L5+E5a comb Filter; Low GDR	Sales
1166.22	1186.68	1176.45	in dev.	new	20.46	1.6	3*3	GNSS L1+E1+G1+B1 / L5+E5a comb Filter; Low GDR	Sales
1559	1607	1583	in dev.	new	48	1.9	3*3	GNSS L1+E1+G1+B1 / E5b+G3+L2+G2 comb Filter; Low GDR	Sales
1196	1250	1223	B3436	new	54	2.0	3*3	GNSS L1+E1+G1+B1 / E5b+G3+L2+G2 comb Filter; Low GDR	Sales
1559	1606	1582.5	in dev.	new	47	2.7	3*3	GNSS L1+E1+G1+B1 / E5b+G3+L2+G2 comb Filter; Low GDR	Sales
1196	1249	1222.5	B39162B2621P810	new	53	2.7	1.5*1.1	GNSS L+L1+E1+G1+B1 / E5b+G3+L2+G2 comb filter; Low GDR	Sales
1525	1606	1565.5	in dev.	new	81	3.1	1.5*1.1	GNSS L1+E1+G1+B1 / E5b+G3+L2+G2 comb filter; Low GDR	Sales
1197	1249	1223	in dev.	new	52	1.6-2.2	1.5*1.1	GNSS L1+E1+G1+B1 / E5b+G3+L2+G2 comb filter; Low GDR	Sales
1559	1606	1582.5	in dev.	new	47	1.4-2.2	1.5*1.1	GNSS L1+E1+G1+B1 / E5b+G3+L2+G2 comb filter; Low GDR; high Attenuation	Sales
1570	1580	1575	B39162B3518H910	o	10	3.8	3*2.5	GPS/Glonass diplexer	Sales
1597	1607	1602	B39162B3518H910	o	10	3.6	3*2.5	GPS/Glonass diplexer	Sales

Filter for GNSS

Start Freq MHz	Stop Freq MHz	Center Freq MHz	Type	Remark	Usable Passband MHz	Insertion Attenuation dB	Package size mm*mm	Application	DS link
----------------	---------------	-----------------	------	--------	---------------------	--------------------------	--------------------	-------------	---------

Extractor / Band Stop filter

Start Freq MHz	Stop Freq MHz	Center Freq MHz	Type	Remark	Usable Passband MHz	Insertion Attenuation dB	Package size mm*mm	Application	DS link
1574.42	1605.89	see DS	B39162B4322P810		see DS	1.6 - 1.8	2*1.6	GPS/Glonass extractor GPS/Glonass bal / Non-GPS/Glonass se	Sales
1574.42	1605.89	see DS	B39162B3405H910		see DS	1.9 - 3.4	3*2.5	GPS/Glonass extractor	Sales
1559.05	1605.89	see DS	B39162B3478H910	new	see DS	1.6 - 2.6	3*2.5	GPS/Glonass/Beidou extractor	Sales
1565.42	1605.89	see DS	B39162B4340P810	new	see DS	1.6 - 2.4	2*1.6	GPS/Glonass/Beidou extractor	Sales
1559.05	1605.89	see DS	B39162B4368P810	new	see DS	1.8 - 2.2	2*1.6	GPS/Glonass/Beidou extractor	Sales
1572.42	1578.42	1575.42	B39162B3470H910	new	6	0.65 - 1.9	3*2.5	GPS band stop filter	Sales

Filter and Duplexer for Telematics Communication (se/se; 50Ω/50Ω)

Band	Function	Remark	Center Frequency MHz	Type	Package size mm*mm	Feature	DS link
1	Duplexer		1950/2140	B39212B4425P810	2.0*1.6	Improved isolation	B4425
	(D)Rx filter		2140	B39212B4358P810	1.4*1.1		B4358
	(D)Rx filter		2140	B39212B4359P810	1.4*1.1	High isolation next to skirt on Tx side	B4359
2	Tx filter		1950	B39202B4309P810	1.4*1.1		B4309
	Duplexer		1880/1960	B39202B4431P810	1.8*1.4		B4431
	(D)Rx filter		1960	B39202B4366P810	1.4*1.1		B4366
3	Tx filter		1880	B39192B4315P810	1.4*1.1		B4315
	Duplexer		1747.5/1842.5	B39182B4421P810	1.8*1.4		B4421
	(D)Rx filter	special	1842.5	B39182B4361P810	1.4*1.1	Temperature compensation	B4361
4	Tx filter		1747.5	B39172B4331P810	1.4*1.1		B4331
	Duplexer		1732.5/2132.5	B39212B4424P810	2.0*1.6		B4424
	(D)Rx filter		2140	B39212B4358P810	1.4*1.1		B4358
5	Tx filter		1732.5	B39172B4307F210	1.4*1.1		B4307
	Duplexer		836.5/881.5	B39881B4422P810	2.0*1.6		B4422
	(D)Rx filter		881.5	B39881B4362P810	1.4*1.1		B4362
5/26	Tx filter		836.5	B39841B4311P810	1.4*1.1		B4311
	(D)Rx filter		876.5	B39781B2601P810	1.1*0.9	small size	B2601
	Duplexer		2535/2655	B39272B4418P810	2.0*1.6		B4418
7	(D)Rx filter		2655	B39272B2602P810	1.1*0.9	small size	B2602
	(D)Rx filter		2655	B39272B4357P810	1.4*1.1		B4357
	Tx filter		2535	B39252B4332P810	1.4*1.1		B4332
8	Duplexer		897.5/942.5	B39941B4432P810	2.0*1.6		B4432
	(D)Rx filter		942.5	B39941B2606P810	1.1*0.9	small size	B2606
	(D)Rx filter	special	942.5	B39941B4356P810	1.4*1.1	B20 co-design, Temperature compensation	B4356
	(D)Rx filter		942.5	B39941B4363P810	1.4*1.1		B4363
	Tx filter		897.5	B39901B4330P810	1.4*1.1		B4330
	Duplexer	new	1438/1486	in dev.	2.0*1.6		
11/21	(D)Rx filter	new	1493.4	in dev.	1.1*0.9		
12/17	Duplexer		707/742	B39741B4414P810	2.0*1.6	including B13 Rx	B4414
	Duplexer		707.5/737.5	B39741B4423P810	2.0*1.6		B4423
	(D)Rx filter		737	B39731B2609P810	1.1*0.9	small size	B2609
	(D)Rx filter		737	B39741B4339P810	1.4*1.1		B4339
	Tx filter		707	B39711B4337P810	1.4*1.1		B4337
	Duplexer		782/751	B39871B4420P810	2.0*1.6		B4420
13	(D)Rx filter		751	B39751B4354P810	1.4*1.1		B4354
	(D)Rx filter		751	B39751B2613P810	1.1*0.9		B2613
	Tx filter		782	B39781B4378P810	2.0*1.6	High power durability (29dBm)	B4378
12/13/17	Tx filter		782	B39781B4319P810	1.4*1.1		B4319
	(D)Rx filter		742.5	B39741B2605P810	1.4*1.1		B2605
	13/14	Tx filter	787.5	B39791B4341P810	1.4*1.1		B4341
14	Duplexer	new	793	in dev.	1.8*1.4		
	(D)Rx filter	new	763	B39761B2626P810	1.1*0.9		B2626
20	Duplexer		847/806	B39851B4428P810	2.0*1.6		B4428
	(D)Rx filter	new	806	in dev.	1.1*1.4		
	(D)Rx filter	special	806	B39811B4355P810	1.4*1.1	B8 co-design, Temperature compensation	B4355
	(D)Rx filter		806	B39811B4369P810	1.4*1.1		B4369
	Tx filter		847	B39851B4320P810	1.4*1.1		B4320
	Duplexer		1455.4/1503.4	B39152B4429P810	2.0*1.6		B4429
21	(D)Rx filter		1503.4	B39152B4374P810	1.4*1.1		B4374
	Duplexer		831.5/876.5	B39871B4430P810	2.0*1.6		B4430
26	(D)Rx filter		876.5	B39871B4376P810	1.4*1.1		B4376
	Duplexer lower		718/773	B39771B4426P810	2.0*1.6		B4426
28	Duplexer upper		733/788	B39791B4427P810	2.0*1.6		B4427
	(D)Rx filter	special	780.5	B39781B4373P810	1.4*1.1	Temperature compensation	B4373
29	(D)Rx filter		722.5	B39721B2603P810	1.1*0.9	small size	B2603
	(D)Rx filter		722.5	B39721B4370P810	1.4*1.1		B4370

Filter and Duplexer for Telematics Communication (se/se; 50Ω/50Ω)

Band	Function	Remark	Center Frequency MHz	Type	Package size mm*mm	Feature	DS link
30	(D)Rx filter	new	2355	B39242 B2604 P810	1.1*0.9	small size	B2604
	(D)Rx filter		2355	B39242 B4371 P810	1.4*1.1		B4371
32	(D)Rx filter		1474	B39152 B4375 P810	1.4*1.1		B4375
33/39+34	(D)Rx filter		1900/2017.5	B39202 B4384 P810	1.5*1.1	2in1	B4384
34	Rx filter		2017.5	in dev.	1.1*0.9		
38	Tx filter		2595	B39262 B4343 P810	1.4*1.1	post-PA	B4343
40	(D)Rx filter		2350	B39242 B4352 P810	1.4*1.1		B4352
	Tx filter		2350	B39242 B4351 P810	2.0*1.6	50 Ω se IN / 50 Ω se OUT	B4351
41	Rx		2593	B39262 B4349 P810	2.0*1.6		B4349
71	Duplexer	new	634.5/680.5	in dev.	2.0*1.6		
	(D)Rx filter	new	634.5	in dev.	1.4*1.1		

Duplexer se/se for High Rx - Tx out-of-band isolation

Band	Function	Remark	Center Frequency	Type	Package size	Feature	
1	Duplexer		1950/2140	B39212 B4408 P810	2.0*1.6		B4408
2	Duplexer		1880/1960	B39202 B4412 P810	2.0*1.6		B4412
3	Duplexer		1747.5/1842.5	B39182 B4411 P810	2.0*1.6		B4411
5	Duplexer		836.5/881.5	B39881 B4416 P810	2.0*1.6		B4416
7	Duplexer		2535/2655	B39272 B4418 P810	2.0*1.6		B4418
8	Duplexer		2535/2655	B39941 B4410 P810	2.0*1.6		B4410
12/17	Duplexer		707/737	B39741 B4413 P810	2.0*1.6		B4413
	Duplexer		707/742	B39741 B4414 P810	2.0*1.6	including B13 Rx	B4414
20	Duplexer		847/806	B39851 B4409 P810	2.0*1.6		B4409

Di-Triplexer for Telematics application

Band	Function	Remark	Center Frequency	Type	Package size	Feature	
1+3	Diplexer		2140 + 1842.5	B39212 B4386 P810	1.5*1.1	optimized for carrier aggregation	Sales
1+3+11/21	Rx filter	new	2140+1842.5+1493.4	B4389	1.8*1.4	Triplexer	Sales
1+3+32	Rx filter	new	2140+1842.5+1474	in dev.	1.8*1.4	Triplexer	Sales
2+4	Diplexer		1960 + 2132.5	B39212 B4385 P810	1.5*1.1	optimized for carrier aggregation	Sales
2/25+4/66	Diplexer	new	1962.5 + 2155	B39222 B4387 P810	1.5*1.1	optimized for carrier aggregation	Sales

Diplexer, band-stop filter and extractor for GNSS, digital radio and metering

Center Frequency MHz	Type	Remark	Usable Passband MHz	Insertion Attenuation dB	Package size mm*mm	Feature	DS link
725.50	B39731 B3473 H910				3*2.5	DVB-T band-stop filter; LTE 700 Tx and Rx suppression	Sales
725.50	B39731 B3477 B510				3*3	LTE 700 Notch	Sales
733.00	B39731 B3476 H910				3*2.5	Band-stop filter ISDB-T LTE 700Tx, band 18	B3476
736.00	B39741 B3481 B510	new			3*3	Band-stop filter for digital TV, band 8, 20, 28 suppression	Sales
753.00	B39751 B3480 B510	new			3*3	Band-stop filter for digital TV, band 8, 20, 28 suppression	Sales
861.00	B39731 B3479 B510				3*3	Band-stop filter ISDB-T; LTE 700Tx, band 18 and 19 suppression	Sales
868.50	B39871 B3448 U510				3*3	Telestart-Extractor; Temperature compensation	Sales
924.30	B39921 B3474 H910				3*2.5	Notch filter for 920 MHz Japan AMI band	Sales
1575.00 2326.25	B39232 B3526 U510		2.048 12.5	1.8 1.6	3*3	GPS/SDARS Diplexer	Sales
1575.00 2332.50	B39232 B3920 U510		6 25	1.2 1.4	3*3	GPS/SDARS Diplexer	Sales
1592.21 2332.50	B39232 B3927 U510		37.58 25	1.5 1.6	3*3	GPS/Glonass/SDARS Diplexer	Sales
2332.50	B39232 B3471 H910				3*2.5	SDARS band-stop filter	Sales
2332.50	in dev.	new			1.5*1.1	SDARS band-stop filter	Sales
2402.50	B39242 B2610 P810	new special			1.5*1.1	Band-stop filter for SDARS and Wifi	Sales
2436.00	B39242 B2612 P810	new special	83.5		1.5*1.1	WLAN notch, 125C, Temperature compensation	Sales

Bandpass filter for Digital Radio
--

Center Frequency MHz	Type	Remark	Usable Passband MHz	Insertion Attenuation dB	Package size mm*mm	Standard	Feature	DS link
1472	B39152B1664U410		40	1.6	3.0*3.0	DMB (DAB), WorldSpace	50Ωse/50Ωse	B1664
1472	B39152B1647U510		40	3.0	3*3	DMB (DAB), WorldSpace	50Ωse/100Ωbal	B1647
1472	B39152B4325P810		40	1.5	1.4*1.1	DMB (DAB), WorldSpace	50Ωse/50Ωse	B4325
1472	B39152B4326P810		40	2.2	1.4*1.1	DMB (DAB), WorldSpace	50Ωse/100Ωbal	B4326
2332.50	B39232B3425U510		25	2.4	3*3	Sirius/XM Satellite Radio	50Ωse/100Ωbal	Sales
2332.50	B39232B1669U410		25	2.4	3*3	Sirius/XM Satellite Radio	50Ωse/50Ωse	Sales
2332.50	B39232B3404U410		25	0.6	3*3	Sirius/XM Satellite Radio	50Ωse/50Ωse; very low IL	Sales
2332.50	B39232B3595U410		25	1.5	3*3	Sirius/XM Satellite Radio	50Ωse/50Ωse	Sales
2332.50	B39232B3442U410	special	25	3.0	3*3	Sirius/XM Satellite Radio	50Ωse/50Ωse Temperature compensation	Sales
2332.50	B39232B3416U410		25	0.47	3*3	Sirius/XM Satellite Radio	50Ωse/50Ωse; low IA	Sales
2332.50	B39232B2622P810	new	25	0.33	3*3	Sirius/XM Satellite Radio	50Ωse/50Ωse	Sales

Resonator for ISM

Center Frequency MHz	Type	Remark	Frequency Tolerance kHz	Frequency Tolerance ppm	Insertion Attenuation dB	Package size mm*mm	DS link
314.90	B39311R 994H110		±25	±79	1.5	3.0*3.0	R 994
315.00	B39321R 901H110		±75	±238	1.5	3.0*3.0	R 901
315.00	B39321R1901A310		±50	±159	1.4	3.0*3.0	R1901
315.00	B39321R1921A310		±25	±79	1.5	3.0*3.0	R1921
315.02	B39321R 993H110		±25	±79	1.5	3.0*3.0	R 993
315.04	B39321R 963H110		±50	±159	1.4	3.0*3.0	R 963
315.50	B39321R 903H110		±75	±238	1.5	3.0*3.0	R 903
319.508	B39321R1952A310		±75	±50	1.5	3.0*3.0	R1952
433.92	in dev.	new	±75	±173	1.4	2.5*2.0	
433.92	B39431R 920H110		±75	±173	1.4	3.0*3.0	R 920
433.92	B39431R1920A310		±25	±58	1.4	3.0*3.0	R1920
433.94	B39431R 992H110		±25	±58	1.5	3.0*3.0	R 992
434.42	B39431R 969H110		±50	±115	1.3	3.0*3.0	R 969
868.35	B39871R1950A310		±150	±173	1.2	3.0*3.0	R1950
915.00	B39921R2906H110		±250	±273	7.2	3.0*3.0	R2906
1176.00	B39122R 959H110		±300	±255	1.3	3.0*3.0	R 959